# μchiller Controller for chillers / heat pumps





# µCH2 SE replacement guide



High Efficiency Solutions

# <u>CAREL</u>

# WARNINGS



CAREL bases the development of its products on decades of experience in HVAC, on continuous investments in technological innovations to products, procedures and strict quality processes with in-circuit and functional testing on 100% of its products, and on the most innovative production technology available on the market. CAREL and its subsidiaries/affiliates nonetheless cannot guarantee that all the aspects of the product and the software included with the product respond to the requirements of the final application, despite the product being developed according to start-of-the-art techniques.

The customer (manufacturer, developer or installer of the final equipment) accepts all liability and risk relating to the configuration of the product in order to reach the expected results in relation to the specific final installation and/or equipment. CAREL may, based on specific agreements, act as a consultant for the successful commissioning of the final unit/application, however in no case does it accept liability for the correct operation of the final equipment/system.

The CAREL product is a state-of-the-art product, whose operation is specified in the technical documentation supplied with the product or can be downloaded, even prior to purchase, from the website www.carel.com.

Each CAREL product, in relation to its advanced level of technology, requires setup/ configuration/programming/commissioning to be able to operate in the best possible way for the specific application. Failure to complete such operations, which are required/indicated in the user manual, may cause the final product to malfunction; CAREL accepts no liability in such cases.

Only qualified personnel may install or carry out technical service on the product. The customer must only use the product in the manner described in the documentation relating to the product.

In addition to observing any further warnings described in this manual, the following warnings must be heeded for all CAREL products:

- Prevent the electronic circuits from getting wet. Rain, humidity and all types of liquids or condensate contain corrosive minerals that may damage the electronic circuits. In any case, the product should be used or stored in environments that comply with the temperature and humidity limits specified in the manual.
- Do not install the device in particularly hot environments. Too high temperatures
  may reduce the life of electronic devices, damage them and deform or melt the
  plastic parts. In any case, the product should be used or stored in environments
  that comply with the temperature and humidity limits specified in the manual.
- Do not attempt to open the device in any way other than described in the manual.
- Do not drop, hit or shake the device, as the internal circuits and mechanisms may be irreparably damaged.
- Do not use corrosive chemicals, solvents or aggressive detergents to clean the device.
- Do not use the product for applications other than those specified in the technical manual.

All of the above suggestions likewise apply to the controllers, serial cards, programming keys or any other accessory in the CAREL product portfolio.

CAREL adopts a policy of continual development. Consequently, CAREL reserves the right to make changes and improvements to any product described in this document without prior warning.

The technical specifications shown in the manual may be changed without prior warning.

The liability of CAREL in relation to its products is specified in the CAREL general contract conditions, available on the website www.carel.com and/or by specific agreements with customers; specifically, to the extent where allowed by applicable legislation, in no case will CAREL, its employees or subsidiaries/affiliates be liable for any lost earnings or sales, losses of data and information, costs of replacement goods or services, damage to things or people, downtime or any direct, indirect, incidental, actual, punitive, exemplary, special or consequential damage of any kind whatsoever, whether contractual, extra-contractual or due to negligence, or any other liabilities deriving from the installation, use or impossibility to use the product, even if CAREL or its subsidiaries/affiliates are warned of the possibility of such damage.



# INFORMATION FOR USERS ON THE CORRECT HANDLING OF WASTE ELECTRICAL AND ELECTRONIC EQUIPMENT (WEEE)

In reference to European Union directive 2002/96/EC issued on 27 January 2003 and related national legislation, please note that:

- 1. WEEE cannot be disposed of as municipal waste and such waste must be collected and disposed of separately;
- the public or private waste collection systems defined by local legislation must be used. In addition, the equipment can be returned to the distributor at the end of its working life when buying new equipment;
- the equipment may contain hazardous substances: the improper use or incorrect disposal of such may have negative effects on human health and on the environment;
- 4. the symbol (crossed-out wheeled bin) shown on the product or on the packaging and on the technical leaflet indicates that the equipment has been introduced onto the market after 13 August 2005 and that it must be disposed of separately;
- 5. in the event of illegal disposal of electrical and electronic waste, the penalties are specified by local waste disposal legislation.

Warranty on materials: 2 years (from production date, excluding consumables).

**Approval:** the quality and safety of CAREL INDUSTRIES Hq products are guaranteed by the ISO 9001 certified design and production system.



**IMPORTANT:** Separate as much as possible the probe and digital input cables from cables to inductive loads and power cables, so as to avoid possible electromagnetic disturbance. Never run power cables (including the electrical panel cables) and signal cables in the same conduits.

# **KEY TO THE SYMBOLS**



**Caution:** to bring critical issues to the attention of those using the product.

**Notice:** to focus attention on important topics; in particular the practical application of the various product functions.

**Caution:** this product is to be integrated and/or incorporated into the final apparatus or equipment. Verification of conformity to the laws and technical standards in force in the country where the final apparatus or equipment will be operated is the manufacturer's responsibility. Before delivering the product, Carel has already completed the checks and tests required by the relevant European directives and harmonised standards, using a typical test setup, which however cannot be considered as representing all possible conditions of the final installation. ENG

CAREL

# CAREL

# Content

1. IN	ITRODUCTION	7
1.1	Main functions	7
2. IN	ISTALLATION	8
2.1	Warnings	8
2.2	Panel version	
2.3	DIN rail version	
2.4	Electrical installation	
2.5	Probe/digital input connection	9
2.6	Connection to user terminals	
2.7	Positioning inside the panel	
2.8	Electrical installation	
2.9	Connecting serial ports with two circuits	
2.10	Source fan speed controller	
2.11	Electronic expansion valve driver	13
. IN	IPUT/OUTPUT CONFIGURATION	14
3.1	Analogue inputs	14
3.2	Digital inputs	14
3.3	Analogue outputs	15
3.4	Digital outputs	15
. A	PPLICATION COMPATIBILITY	16
4.1	Air/air	
4.2	Reverse-cycle air/air units	
4.3	Air/water chillers	
4.4	Reverse-cycle air/water units	21
4.5	Air/water chillers	
4.6	Reverse-cycle water/water units	
4.7	Air-cooled condensing unit	25
4.8	Reverse-cycle air-cooled condensing unit	
4.9	Water-cooled condensing unit	27
4.10	Reverse-cycle water-cooled condensing unit	
. C	OMMISSIONING	30
5.1	APPLICA app	
5.2	Config. procedure - Legacy model	
5.3	Unit set-up parameter list	
5.4	Applica Desktop	
5.5	Configuration procedure with Applica Desktop Legacy Model	

ENG

CAREL

# 1. INTRODUCTION

This guide has been created with the aim of supporting uChiller users for replacement in the field of the microchiller2 SE (hereinafter mCH2 SE) with the new product (hereinafter Legacy model).

# This document contains specific information on the Legacy models. For other functions, see the $\mu$ Chiller manual +0300053\*\* rel. 1.3 and higher.

List of Legacy models and dedicated accessories used to replace mCH2 SE.

P/N	Assembly	Connectivity	Compressor manage- ment:	Remarks	Electronic valve management
UCHBP000X0190	panel	NFC	On/Off	standard version	bipolar: with EVD Evolution driver
UCHBP000X0200	panel	NFC, Bluetooth (BLE)	On/Off	standard version	bipolar: with EVD Evolution driver
UCHBD000X1230	DIN rail	-	On/Off	standard version	bipolar: with EVD Evolution driver
					Tab. 1.a

Accessory P/N	Description	
UCHCONPMC0	Adapter kit for MCH2	
		Tab. 1.b

Below is the list of MCH2 and MCH2-SE products and I/O expansions that can be replaced with the new uChiller

Part number	Description	Replacement product
MCH200000*	MICROCHILLER 2 B.IN VERS,1 CIRCUIT, 2 COMPRES.	UCHBP000X0190 / UCHBP000X0200
MCH200003*	MCH 2 SE MAX 1 CIRC. 2 COMPR.	UCHBP000X0190 / UCHBP000X0200
MCH200103*	MCH 2 SE MAX 1 CIRC. 2 COMPR. + RTC	UCHBP000X0190 / UCHBP000X0200
MCH201000*	MICROCHILLER 2 MAX 1 CIRC. 2 COMPR. WITH NEUTRAL PLASTIC	UCHBP000X0190 / UCHBP000X0200
MCH201003*	MCH 2 SE MAX 1 CIRC. 2 COMPR. WITHOUT LOGO	UCHBP000X0190 / UCHBP000X0200
MCH201103*	MCH 2 SE MAX 1 CIRC. 2 COMPR. + RTC WITHOUT LOGO	UCHBP000X0190 / UCHBP000X0200
MCH200001*	MICROCHILLER 2 DIN VERS, 1 CIRCUIT, 2 COMPRES.	UCHBD000X1230
MCH200002*	MICROCHILLER 2 EXPANS. MAX 2 CIRC. 4 COMPR.	UCHBE00001230

Tab. 1.c

# 1.1 Main functions

Ref.	Description		
Main features	Up to two circuits and 2 + 2 compressors		
	Tandem compressor configuration		
	Air/water (A/W) and water/water chiller or heat pump		
	Air/air unit (A/A)		
	Condensing unit (MC)		
	Up to 2 evaporators per unit		
Hardware	Panel mounting model		
	DIN rail model		
User interface	7-segment, 2-row LED display, optional pGDx graphic display, communication via APPLICA app (compatible with NFC and BTLE)		
	for mobile devices		
Temperature control	PID at start-up		
	PID in operation		
	Set point compensation on outdoor temperature		
Compressor rotation	FIFO or timed		
Compressor management	Generic scroll compressors		
Circuit destabilisation	Forced compressor rotation (extended operation at part load)		
Electronic valve driver	External driver management via FieldBus port (all versions)		
Programming with time	Unit ON-OFF or 2nd set point (1 time band per day)		
bands	"Noise reduction" function for condenser fans (1 time band per day)		
System pumps	1/2 pumps (2 pumps only with 2 circuits)		
o)occin panipo	Rotation by time or with pump overload alarm		
	Cyclical activation during standby		
Water-cooled condenser	1 common pump for both circuits		
Air-cooled condenser	Independent fans on each circuit or common to both circuits		
	Fan modulation based on condensing temperature (On/Off fan control via relay or CAREL CONVONOFF0 module)		
	Optimised start-up to quickly bring the compressor(s) to steady operation		
	Fan anti-block protection (harsh climate)		
Defrost	Simultaneous		
Denose	Separate		
	Independent		
	Only when the fans are used		
	Defrost interval managed based on outside temperature ("sliding defrost")		
Prevent	Prevention of scroll compressor operating limits in relation to condensing and evaporation temperature		
	Evaporator frost prevention		
Alarms	Management of automatic and manual reset according to alarm severity		
(see the chapter on Alarms)	Alarm log (up to 20 events): alarm and reset date and time recorded		
Connectivity/supervision	RS485 serial port		
connectivity/supervision	Modbus RTU		
	Baud rate up to 115200 bit/s		
	Frame configurable by Parity (None, Even, Odd) and StopBits (1 or 2); Databits fixed at 8 bits.		
	ברימות בסוווקטונטוב טיר מונץ (מסוב, ביכוד, סטט) מוט אנסטונג (דטר 2), סמנטונג וואכט מרט טונג.		

# 2. INSTALLATION

## 2.1 Warnings

**Caution:** avoid installing the controller in environments with the following characteristics:

- temperature and humidity that do not comply with the ambient operating conditions (see "Technical specifications");
- strong vibrations or knocks;
- exposure to water sprays or condensate;
- exposure to aggressive and polluting atmospheres (e.g.: sulphur and ammonia gases, saline mist, smoke) which may cause corrosion and/ or oxidation;
- strong magnetic and/or radio frequency interference (thus avoid installation near transmitting antennae);
- exposure to direct sunlight and the elements in general;
- wide and rapid fluctuations in ambient temperature;
- exposure to dust (formation of corrosive patina with possible oxidation and reduction of insulation).

# 2.2 Panel version

# 2.2.1 Dimensions in mm (inches)



#### 2.2.2 Assembly

**Caution:** before carrying out any maintenance, disconnect the controller from the power supply by moving the main system switch to "off".



- Place the controller in the opening, pressing lightly on the side anchoring tabs.
- 2. Then press on the front until fully inserted (the side tabs will bend, and the catches will attach the controller to the panel).

**Caution:** IP65 front protection is guaranteed only if the following conditions are met:

- maximum deviation of the rectangular opening from flat surface:  $\leq$  0.5 mm;
- thickness of the electrical panel sheet metal: 0.8-2 mm;
- maximum roughness of the surface where the gasket is applied:  $\leq$  120  $\mu m.$

Notice: the thickness of the sheet metal (or material) used to make the electrical panel must be adequate to ensure safe and stable mounting of the product..

#### 2.2.3 Assembly



Open the electrical panel from the rear and press the anchoring tabs and then the controller to remove it.

- 1. Gently press the side anchoring tabs on the controller;
- 2. Exert slight pressure on the controller until it is removed.

**Caution:** the operation does not require the use of a screwdriver or other tools.

# 2.3 DIN rail version

#### 2.3.3 Dimensions - mm (in)



Apply slight pressure to the controller resting on the DIN rail until the rear tab clicks into place.

### 2.3.4 Assembly

Use a screwdriver as a lever in the hole to lift and release the tab. The tab is held in the locked position by return springs.

# 2.4 Electrical installation

**Caution:** before carrying out any maintenance, disconnect the controller from the power supply by moving the main system switch to "off".

#### 2.4.1 Adapter kit for MCH2



Using the UCHCONPMC0 adapter kit, installers can replace the mCH2 SE with the corresponding uCH legacy model in just a few minutes, utilising the existing wiring in the unit's electrical panel.

\*\*NDR : l'immagine è presente nella news uChiller 2021\_04\_30 If the adapter kit is not available, see the following paragraphs.

## 2.4.2 Description of the terminals

#### Panel model



Fig. 2.d

#### DIN rail model

Basic



Fig. 2.e

# 2.5 Probe/digital input connection

NTC probes



ENG

4-20 mA probes/digital inputs



Fig. 2.g



### 0-5 V ratiometric pressure probes



Notice: O = GND

Fig. 2.i

Ref.	Desc	ription
J1	G	Power supply
	G0	Power supply: reference
J2	5V	Ratiometric probe power supply
	S3	Analogue input 3
	S1	Analogue input 1
	Y1	Analogue output 1
	ID1	Digital input 1
	0	GND: reference for probes, digital inputs and analogue
		outputs
	S5	Analogue input 5
	S2	Analogue input 2
	Y2	Analogue output 2
	ID2	Digital input 2
J3	ID3	Digital input 3
	ID5	Digital input 5
	+V	Power supply to 4-20 mA active probes
	S6	Analogue input 6
	VL	Not used
	ID4	Digital input 4
	0	GND: reference for analogue and digital inputs
	S4	Analogue input 4
J4	-	BMS serial port (RS485): Rx-/Tx-
	+	BMS serial port (RS485): Rx+/Tx+
	0	BMS serial port (RS485): GND
J5	-	Fieldbus serial port (RS485): Rx-/Tx-
	+	Fieldbus serial port (RS485): Rx+/Tx+
	0	Fieldbus serial port (RS485): GND
JG	С	Common for relays 1, 2, 3.4
	NO1	Digital output (relay) 1
	NO2	Digital output (relay) 2
	NO3	Digital output (relay) 3
	NO4	Digital output (relay) 4
J7	С	Common for relay 5
	NO5	Digital output (relay) 5
J8	-	Unit terminal connector (AX5* or PGR04*)
J9	S7	Analogue input 7
	ID6	Digital input 6
	0	Input reference
	0	Input reference
J11	-	(not used)
	С	Common for relay 6
	NO6	Digital output (relay) 6

Tab. 2.a

2.6.2

# CAREL

# 2.6 Connection to user terminals

#### 2.6.1 Panel model

**DIN rail model** 

нананьвнаная

pehiller

กกกกกกกกกกกก J4 💷

18



User terminal

2

۲

#### Connection to connector J4



Connection to connector J8



Fig. 2.m

Notice 2: in cases (1) and (4), set the BMS port communication parameters as shown in the table:

Fig. 2.k

#### Communication parameters

User	Display	P/N	Description	Value	Min	Max	UOM
S	X	Hd00	BMS: serial address	1	1	247	-
S	x	Hd01	BMS: baud rate	6	3	7	-
			3=9600; 4=19200; 5=38400;				
			6=57600; 7=115200				
S		Hd02	BMS: settings	0	0	5	-
			0=8-NONE-1; 1=8-NONE-2; 2=8-EVEN-1				
			3=8-EVEN-2; 4=8-ODD-1; 5=8-ODD-2				
							Tab. 2.b

# 2.7 Positioning inside the panel

The position of the controller in the electrical cabinet must be chosen so as to guarantee correct physical separation from the power components (solenoids, contactors, actuators, inverters, ...) and the connected cables. Proximity to such devices/cables may create random malfunctions that are not immediately evident. The structure of the panel must allow the correct flow of cooling air.

# 2.8 Electrical installation

**Caution:** When laying the wiring, "physically" separate the power part from the control part. The proximity of these two sets of wires will, in most cases, cause problems of induced disturbance or, over time, malfunctions or damage to the components. The ideal solution is to house these two circuits in two separate cabinets. Sometimes this is not possible, and therefore the power part and the control part must be installed in two separate areas inside the same panel.

For the control signals, it is recommended to use shielded cables with twisted wires. If the controller cables have to cross over the power cables, the intersections must be as near as possible to 90 degrees, always avoiding running the controller cables parallel to the power cables.

Pay attention to the following warnings:

- use cable ends suitable for the corresponding terminals. Loosen each screw and insert the cable ends, then tighten the screws. When the operation is completed, slightly tug the cables to check they are sufficiently tight;
- separate as much as possible the probe signal, digital input and serial line cables from the cables carrying inductive loads and power cables to avoid possible electromagnetic disturbance. Never run power cables (including the electrical cables) and probe signal cables in the same conduits. Do not install the probe cables in the immediate vicinity of power devices (contactors, circuit breakers or similar);
- reduce the path of the probe cables as much as possible, and avoid spiral paths that enclose power devices;
- avoid touching or nearly touching the electronic components fitted on the boards to avoid electrostatic discharges (extremely damaging) from the operator to the components;
- do not secure the cables to the terminals by pressing the screwdriver with excessive force, to avoid damaging the controller: maximum tightening torque: 0.22-0.25 N·m. For applications subject to considerable vibrations (1.5 mm pk-pk 10/55 Hz), secure the cables connected to the controller around 3 cm from the connectors using clamps;

 all the extra low voltage connections (analogue and digital inputs, analogue outputs, serial bus connections, power supplies) must have reinforced or double insulation from the mains network.

# 2.9 Connecting serial ports with two circuits

For serial connections (FBus and BMS ports), the cables used must be suitable for the RS485 standard (shielded twisted pair, see the specifications in the following table). The earth connection of the shield must be made using the shortest connection possible on the metal plate at the bottom of the electrical panel.

Master device		Lmax (m)	Wire/ wire capac- itance (pF/m)	Resistance on first and last device	Max no. slave devic- es on bus	Data rate (bit/s)
μChiller	FBus	10	<90	120 Ω	16	19200
PC	BMS	500	<90	120 Ω	16	115200
(super- vision)						

Tab. 2.c

ENG

Notice: 120  $\Omega$  1/4W terminating resistors on the first and last devices in the network must be used when the length exceeds 100 m.

For two-circuit units, the power supply connections must be in phase between the two controllers (G0 on the master controller and G0 on the slave controller connected to the same power supply wire); the serial connection between the two controllers (J5 FBus on the master and J4 BMS on the slave) must be made as shown in the figure (+ with + and - with -).



# 2.10 Source fan speed controller

The typical connections on mCH2 / mCH2 SE to manage the source fans and how these change with the new mChiller are shown below.

#### Case 1: ON-OFF fan management



ON/OFF management of condensing fans is possible by using the CONVONOFF0 module connected to mCH2 / mCH2 SE.

The control relay has a switchable power of 10 A at 250 Vac in AC1 (1/3 HP inductive).

Operation is similar with the new uCHiller. To manage the condensing fan in this mode, simply connect terminals 3 and 4 on the CONVONOFF0 module to terminals Y1 and GND (connector J2) on the UCHB\*000X\*\*\*\*.

Case 2: PWM fan speed management (MCHRTF\*)

GND



Fig. 2.p

The MCHRTF\* single-phase voltage regulators use the phase cutting principle to regulate the effective output voltage to the load, based on the phase  $\alpha$  of the control PWM signal.

The command from mCH2 / mCH2 SE is sent by connecting terminals Y and GND on MCHRTF\* to the corresponding terminals on mCH2 / mCH2.

Specifically, when replacing mCH2 / mCH2 SE, the installer also needs to replace the MCHRTF\* device, as the new uChiller manages 0-10 Vdc speed controllers to ensure higher precision and greater immunity to interference.

The following table shows the replacement models for MCHRTF\*

Part number	Description	Replacement product
MCHRTF04C0	Fan speed controller-cut phase PWM	FCSM042300
	4A/230Vac Faston	
MCHRTF08C0	Fan speed controller-cut phase PWM	FCSM082300
	8A/230Vac Faston	
MCHRTF12C0	Fan speed controller-cut phase PWM	FCSM122300
	12A/230Vac Faston	
		Tab. 2.a

### Case 3: 0-10 Vdc fan speed management



The CONV0/10A0 module converts the PWM signal into a standard 0-10 Vdc (or 4-20 mA) signal.

This module is required if needing to use a non-Carel speed controller.

With the new uCHiller, to manage the condensing fan in this mode, simply remove the CONV0/10A0 module and connect the wires from terminals 5 and 6 on the CONV0/10A0 module to terminals Y1 and GND (connector J2) on UCHB\*000X\*\*\*\*.

### Case 4: Fan speed management with FCS\* module



mCH2 / mCH2SE can directly manage single-phase and three-phase FCS\* speed controllers.

In this case, the "IN+" and "IN-" terminals on FCS\* are connected to terminals "Y" and "GND" on mCH2 / mCH2 SE respectively

# CAREL





With the new uCHiller, to manage the condensing fan in this mode, simply connect the wires from the "IN+" and "IN-" terminals on FCS\* to terminals "Y" and "GND" (connector J2) on UCHB\*000X\*\*\*\*. Pin-strip JP7 also needs to be set to 0-10 Vdc mode (as shown in the image on the side).

# 2.11 Electronic expansion valve driver



mCH2 / mCH2 SE, when connected to the EVD4\* driver can manage electronic expansion valves via the tLAN serial line.

When replacing mCH2 / mCH2 SE, the installer should also replace the EVD4\* device, as EVD4\* is now obsolete and no longer supported by Carel.

The EVD4\* driver should be replaced with EVD EVO.

**Notice:** for information regarding the connections and the configuration of EVD EVO, see the corresponding product manual.

# 3. INPUT/OUTPUT CONFIGURATION

Information on how to configure the  $\mu Chiller$  Legacy inputs and outputs to replace mCH2 and mCH2 SE is shown below.

#### Panel mounting model





DIN rail model (Basic)



Fig. 3.b

# 3.1 Analogue inputs

The analogue inputs on  $\mu$ Chiller Legacy are divided into four groups, according to the type of sensor connected. The groups and the list of parameters used to configure the different analogue inputs are shown below:

Group	Sensor	Master	Slave
		config. parameter	config. parameter
GRP1	S1	HC31	HC41
	S2	HC32	HC42
	S3	HC00	HC43
GRP2	S4	HC34	HC44
	S5	HC35	HC45
GRP3	S6	HC03	HC05
GRP1*	S7*	HC04*	HC47
			Tab. 3.a

(\*) available only on DIN version

The meanings assigned to the analogue inputs according to the various groups for the Master controller (circuit 1) are as follows:

Value	GRP1	GRP2	GRP3
0	Not used	Not used	Not used
1	Source water delivery	Source water delivery	Source water deliver
	temp.	temp.	temp.
2	Outside temperature	Outside temperature	Outside temperature
3	Discharge	Discharge	Remote set point
	temperature circuit 1	temperature circuit 1	
4	Condensing	Condensing	Discharge tempera-
	temperature circ. 1	temperature circ. 1	ture circuit 1
5	Suction	Suction	Condensing
	temperature circ. 1	temperature circ. 1	temperature circ. 1
6	Evaporation	Evaporation	Suction
	temperature circ. 1	temperature circ. 1	temperature circ. 1
7	System water	Condensing	Evaporation
	return temperature	pressure circ. 1	temperature circ. 1
8	System water deliv-	Evaporation	Condensing
	ery temp.	pressure circ. 1	pressure circ. 1
9		System water	Evaporation
		return temperature	pressure circ. 1
10		System water deliv-	System water
		ery temp.	return temperature
11			System water deliv-
			ery temp.
			Tab. 3.

The meanings assigned to the analogue inputs according to the various groups for the Slave controller (circuit 2) are as follows:

GRP1	GRP2	GRP3
Not used	Not used	Not used
Source water delivery	Source water delivery	Source water delivery
temp.	temp.	temp.
Outside temperature	Outside temperature	Outside temperature
Discharge	Discharge	Remote set point
temperature circuit 2	temperature circuit 2	
Condensing	Condensing	Discharge
temperature circ. 2	temperature circ. 2	temperature circuit 1
Suction	Suction	Condensing
temperature circ. 2	temperature circ. 2	temperature circ. 1
Evaporation	Evaporation	Suction
temperature circ. 2	temperature circ. 2	temperature circ. 1
Common water	Condensing	Evaporation
delivery temperature	pressure circ. 2	temperature circ. 1
Evap. water delivery	Evaporation	Condensing
temp. 2	pressure circ. 2	pressure circ. 2
	Common water	Evaporation
	delivery temperature	pressure circ. 2
	Evap. water delivery	Common water
	temp. 2	delivery temperature
		Evaporation
		pressure circ. 2
	Not used Source water delivery temp. Outside temperature Discharge temperature circuit 2 Condensing temperature circ. 2 Suction temperature circ. 2 Evaporation temperature circ. 2 Common water delivery temperature Evap. water delivery	Not used         Not used           Not used         Not used           Source water delivery         Source water delivery           Temp.         Outside temperature           Outside temperature         Discharge           bischarge         Discharge           temperature circuit 2         temperature circuit 2           Condensing         Condensing           temperature circ. 2         temperature circ. 2           Suction         Suction           temperature circ. 2         temperature circ. 2           Evaporation         Evaporation           temperature circ. 2         temperature circ. 2           Common water         Condensing           delivery temperature         pressure circ. 2           Evap. water delivery         Evaporation           temp. 2         pressure circ. 2           Common water         delivery temperature           delivery temperature         pressure circ. 2           Evaporation         temperature circ. 2

Tab. 3.c

# 3.2 Digital inputs

Below is the list of parameters used to configure the digital inputs:

Digital	Master	Slave	
input	configuration parameter	configuration parameter	
ID1	HC14	HC16	
ID2	HC15	HC17	
ID3	High pressure	High pressure	
	switch circ. 1	switch circ. 2	
ID4	HC06	HC09	
ID5	HC07	HC10	
ID6*	HC08*	HC11	

(\*) available only on DIN version

Tab. 3.d

The digital input configuration parameters can have the following meaning:

Value	Master description (circuit 1)	Slave description (circuit 2)
0	Not used Not used	
1	System pump flow switch	System pump flow switch
2	Comp. 1 thermal protector circ. 1	Comp. 1 thermal prot circ. 2
3	Comp. 2 thermal protector circ. 1	Comp. 2 thermal prot. circ. 2
4	Remote on/off	Remote on/off
5	Cooling/heating	Cooling/heating
6	2nd set point 2nd set point	
7	Remote alarm Remote alarm	
8	System pump 1 thermal pro- System pump 1 thermal	
	tector	protector
9	Low pressure switch circ. 1	Low pressure switch circ. 2
10	System pump 2 thermal pro-	System pump 2 thermal
	tector	protector
11**	Comp. 1 request circ. 1	Comp. 1 request circ. 2
12**	Comp. 2 request circ. 1	Comp. 2 request circ. 2
	· · ·	Tab. 3.e

(\*\*) available only for condensing units

3.3 Analogue outputs

Below is the list of parameters used to configure the analogue outputs:

Analogue	Master	Slave
output	configuration parameter	configuration parameter
Y1	HC71	HC81
Y2	HC72	HC82
		Tab. 3.f

The analogue input configuration parameters can have the following meaning:

Value	Master description (circuit 1)	Slave description (circuit 2)
0	Not used	Not used
1	On-off source	On-off source
	fan/pump circ. 1	fan/pump circ. 2
2	Modulating source	Modulating source
	fan circ. 1	fan circ. 2
3	Free cooling	Free cooling
		TLO

Tab. 3.g

# 3.4 Digital outputs

Below is the list of parameters used to configure the digital outputs:

Digital	Master	Slave
input	configuration parameter	configuration parameter
NO1	HC51	HC61
NO2	HC52	HC62
NO3	HC53	HC63
NO4	HC54	HC64
NO5	HC55	HC65
NO6*	HC56	HC66
		Tab. 3.h

(\*) available only on DIN version

The digital output configuration parameters can have the following meaning:

.

Value	Master description (circuit 1)	Slave description (circuit 2)
0	Not used	Not used
1	Compressor1 circuit 1	Compressor1 circuit 2
2	Compressor 2 circuit 1	Compressor 2 circuit 2
3	System heater 1	System heater 2
4	System pump 1 /	System pump 2
	system fan	
5	Source pump / fan	Source pump / fan
6	Frost protection heater	Frost protection heater
	evaporator 1	evaporator 2
7	4-way valve circuit 1	4-way valve circuit 2
8	Oil equalisation	Oil equalisation
	valve circuit 1	valve circuit 2
9	Freecooling valve	
10	General alarm	
11	System pump 2	
12	System heater 2	

15

# 4. APPLICATION COMPATIBILITY

Below is a summary table for the correct configuration of the unit type on uChiller, starting from parameter Hd01 on uCh2 and uCH2SE.

uChiller Legacy parameter key U077 : Type of unit S068 : Source type (FALSE = Air, TRUE = Water) ModE : Cooling/heating mode from keypad (FALSE = Cooling TRUE = Heating)

uCH2se	uChiller (legacy)		
H01	U077	S068	ModE
0 = air-air unit	5		
1 = air-air heat pump	6		FALSE = CH
			TRUE = HP
2 = air-water chiller	0	FALSE	
3 = air-water heat pump	2	FALSE	FALSE = CH
			TRUE = HP
4 = water-water chiller	0	TRUE	
5 = water-water heat pump with reverse-cycle on gas circuit	2	TRUE	FALSE = CH
			TRUE = HP
6 = water-water heat pump with reverse-cycle on water circuit	7	TRUE	FALSE = CH
			TRUE = HP
7 = condensing unit	3	FALSE	
8 = condensing unit with reverse-cycle	4	FALSE	FALSE = CH
· · ·			TRUE = HP
9 = water-cooled condensing unit	3	TRUE	
10 = water-cooled condensing unit with reverse-cycle	4	TRUE	FALSE = CH
- '			TRUE = HP
11 = air-air cooling only unit with electric heating			
	· · · · ·		Tab. 4.a

# 4.1 Air/air

## 4.1.1 Single circuit



#### Key:

1	condenser fan thermal protector		
2	condenser fan		
3	condenser probe		
4	supply probe		
5	heater		
6	evaporator		
7	supply fan thermal protector		
8	supply fan		
9	compressor 1		
10	high pressure		
11	compressor thermal protector		
12	low pressure		
13	room probe		
14	compressor 2		

# 4.1.2 Two circuits



Key:	
1	condenser fan 1 & 2 thermal protector
2	fan
3	condenser probe
4	supply probe
5	heater 1 & 2
6	evaporator 1 & 2
7	supply fan thermal protector
8	supply fan
9	compressor 1 circuit 1
10	high pressure 1 & 2
11	compressor 1 & 2 thermal protector
12	low pressure 1 & 2
13	room probe
14	compressor 2 circuit 1
15	compressor 1 circuit 2
16	compressor 2 circuit 2

# 4.1.3 Two circuits, 1 condensing ventilation circuit



Key:	
1	condenser fan thermal protector
2	fan
2 3 4 5 6	condenser probe 1 & 2
4	supply probe
5	heater 1 & 2
	evaporator 1 & 2
7 8	supply fan
8	room probe
9	compressor 1 circuit 1
10	high pressure 1 & 2
11	compressor 1 & 2 thermal protector
12	low pressure 1 & 2
13	compressor 1 circuit 1
14	compressor 1 circuit 2
15	compressor 2 circuit 2

# 4.2 Reverse-cycle air/air units

# 4.2.1 Single circuit



1	condenser fan thermal protector
2	fan
2 3	condenser probe
4	supply probe
5	heater
6 7	evaporator
7	supply fan thermal protector
8	supply fan
9	compressor 1
10	high pressure
11	compressor thermal protector
12	low pressure
13	room probe
14	compressor 2
15	reversing valve

### 4.2.2 Two circuits



1/	
Key:	
1	condenser fan 1 & 2 thermal protector
2 3 4 5 6 7	fan
3	condenser probe
4	supply probe
5	heater 1 & 2
6	evaporator 1 & 2
7	supply fan thermal protector
8	supply fan
9	compressor 1 circuit 1
10	high pressure 1 & 2
11	compressor 1 & 2 thermal protector
12	low pressure 1 & 2
13	room probe
14	compressor 2 circuit 1
15	reversing valve
16	compressor 1 circuit 2
17	compressor 2 circuit 2

# 4.2.3 Two circuits, 1 condensing ventilation circuit



Key:	
1	condenser fan thermal protector
2	fan
2 3 4 5 6 7 8	condenser probe 1 & 2
4	supply probe
5	heater 1 & 2
6	evaporator 1 & 2
7	supply fan thermal protector
8	supply fan
9	compressor 1 circuit 1
10	high pressure 1 & 2
11	compressor 1 & 2 thermal protector
12	low pressure 1 & 2
13	room probe
14	compressor 2 circuit 1
15	reversing valve
16	compressor 1 circuit 2
17	compressor 2 circuit 2

ENG

# 4.3 Air/water chillers

# 4.3.1 Single circuit



#### Key:

1	condenser fan thermal protector
2	fan
3	condenser probe
4	flow switch
5	evaporator outlet probe
6	evaporator
7	frost protection heater
8	evaporator inlet probe
9	compressor 1
10	high pressure
11	compressor thermal protector
12	low pressure
13	water pump
14	compressor 2



1	condenser fan 1 & 2 thermal protector
2	fan
3	condenser probe
2 3 4 5 6 7 8 9	flow switch
5	common evaporator outlet probe
6	evaporator 1 & 2
7	evaporator outlet probe 1 & 2
8	frost protection heater 1 & 2
	compressor 1 circuit 1
10	high pressure 1 & 2
11	compressor 1 & 2 thermal protector
12	low pressure 1 & 2
13	room probe
14	compressor 2 circuit 1
15	water pump
16	compressor 1 circuit 2
17	compressor 2 circuit 2

### 4.3.3 Two circuits, 1 condensing ventilation circuit



Key:	
1	condenser fan thermal protector
2	fan
3	condenser probe 1 & 2
4	flow switch
5	supply temperature probe
6	evaporator 1 & 2
7	evaporator outlet probe 1 & 2
8	frost protection heater 1 & 2
9	compressor 1 circuit 1
10	high pressure 1 & 2
11	compressor 1 & 2 thermal protector
12	low pressure 1 & 2
13	evaporator inlet probe
14	compressor 2 circuit 1
15	water pump
16	compressor 1 circuit 2
17	compressor 2 circuit 2

# 4.4 Reverse-cycle air/water units

# 4.4.1 Single circuit



Key:	
1	condenser fan thermal protector
2	fan
3	condenser probe
4	flow switch
5	evaporator outlet probe
6	evaporator
7	frost protection heater
8	evaporator inlet probe
9	compressor 1
10	high pressure
11	compressor thermal protector
12	low pressure
13	room probe
14	compressor 2

4.4.2 Two circuits, 2 condensing ventilation circuits



Key:	
1	condenser fan 1 & 2 thermal protector
2 3 4 5 6 7 8 9 10	fan
3	condenser probe
4	flow switch
5	common evaporator probe
6	evaporator 1 & 2
7	evaporator outlet probe 1 & 2
8	supply fan
9	compressor 1 circuit 1
10	high pressure 1 & 2
11	compressor 1 & 2 thermal protector
12	low pressure 1 & 2
13	evaporator inlet probe 1 & 2
14	compressor 2 circuit 1
15	water pump
16	reversing valve
17	compressor 1 circuit 2
18	compressor 2 circuit 2

# 4.4.3 Two circuits, 1 condensing ventilation circuit



Key:	
1	condenser fan 1 & 2 thermal protector
2	fan
3	condenser probe
4	flow switch
2 3 4 5 6 7 8 9	common evaporator probe
6	evaporator 1 & 2
7	evaporator outlet probe 1 & 2
8	supply fan
9	compressor 1 circuit 1
10	high pressure 1 & 2
11	compressor 1 & 2 thermal protector
12	low pressure 1 & 2
13	evaporator inlet probe 1 & 2
14	compressor 2 circuit 1
15	water pump
16	reversing valve
17	compressor 1 circuit 2
18	compressor 2 circuit 2

# 4.5 Air/water chillers

# 4.5.1 Single circuit



### Key:

1	cond. water temperature probe
2	condenser
3	flow switch
4	evaporator outlet probe
5	evaporator
6	frost protection heater
7	evaporator inlet probe
8	compressor 1
9	high pressure
10	compressor thermal protector
11	low pressure
12	water pump
13	compressor 2
14	compressor 2

# 4.5.2 Two circuits, 1 evaporator



Key:	
1	Cond. water temperature probe 1 & 2
2	Condenser 1 & 2
3	flow switch
4	evaporator outlet probe
3 4 5 6	evaporator
6	frost protection heater
7	Compressor 1 circuit 1
8	High pressure 1 & 2
9	Compressor 1 & 2 thermal protector
10	Low pressure 1 & 2
11	Evaporator inlet probe
12	Water pump
13	Compressor 2 circuit 1
14	Compressor 1 circuit 2
15	Compressor 2 circuit 2

# 4.5.3 Two circuits, 2 evaporators



Key:	
1	Cond. water temperature probe 1 & 2
2	Condenser 1 & 2
3	flow switch
2 3 4 5 6	common evaporator outlet probe
5	evaporator outlet probe 1 & 2
	frost protection heater 1 & 2
7	Evaporator 1 & 2
8	Water pump
9	Compressor 1 circuit 1
10	High pressure 1 & 2
11	Compressor 1 & 2 thermal protector
12	Low pressure 1 & 2
13	Compressor 1 circuit 2
14	Compressor 2 circuit 1
15	Compressor 2 circuit 2

#### **Reverse-cycle water/water units** 4.6

#### 4.6.1 Single circuit



Key:	
1	Cond. water temperature probe
2	condenser
3	flow switch
4	Evaporator outlet probe
5	evaporator
6	Reversing valve
7	Evaporator inlet probe
8	compressor
9	High pressure
10	compressor thermal protector
11	Low pressure
12	Water pump
13	Compressor 2

#### 4.6.2 **Two circuits**



# Key: cond. water temperature probe 1 & 2 condenser 1 & 2 flow switch

2

3	flow switch
4 5 6	evaporator outlet probe
5	evaporator outlet probe 1 & 2
6	evaporator 1 & 2
7	frost protection heater 1 & 2
8 9	water pump
9	compressor 1 circuit 1
10	high pressure 1 & 2
11	compressor 1 & 2 thermal protector
12	low pressure 1 & 2
13	evaporator inlet probe
14	compressor 2 circuit 1
15	compressor 1 circuit 2
16	reversing valve 1 & 2
17	compressor 2 circuit 2



Key:	
1	condenser probe 1 & 2
2	condenser 1 & 2
3	flow switch
2 3 4 5 6	evaporator outlet probe
5	evaporator
6	frost protection heater 1 & 2
7	compressor 1 circuit 1
8	high pressure 1 & 2
9	compressor 1 & 2 thermal protector
10	low pressure 1 & 2
11	evaporator inlet probe
12	water pump
13	compressor 2 circuit 1
14	reversing valve 1 & 2
15	compressor 1 circuit 2
16	compressor 2 circuit 2

# 4.7 Air-cooled condensing unit

# 4.7.1 Single circuit



Fig. 4.s

Key:	
1	con

1	condenser fan thermal protector
2	fan
3	condenser probe
4	compressor 1
5	high pressure
6	compressor thermal protector
7	low pressure
8	compressor 2

# ENG

#### 4.7.2 **Two circuits** (1)(2)(2) B7/8 B3/4 9 4 Key: 1 condenser fan thermal protector fan 2 condenser probe 3 6 7 (5 $_{2}(6)$ $(7)_{2}$ 4 compressor 1 circuit 1 high pressure 1 & 2 compressor 1 & 2 thermal protector low pressure 1 & 2 compressor 2 circuit 1 5 6 7 8 9 10 compressor 1 circuit 2 compressor 2 circuit 2 Fig. 4.t

# 4.8 Reverse-cycle air-cooled condensing unit

# 4.8.1 Single circuit



Key:	
1	condenser fan thermal protector
2	fan
3	condenser probe
4	compressor 1
5	high pressure
6	compressor thermal protector
7	low pressure
8	compressor 2
9	reversing valve

# 4.8.2 Two circuits, 1 condensing ventilation circuit



Key:	
1	condenser fan thermal protector
2	fan
3	condenser probe
4 5	compressor 1 circuit 1
5	high pressure 1 & 2
6	compressor 1 & 2 thermal protector
7	low pressure 1 & 2
8	compressor 2 circuit 1
9	compressor 1 circuit 2
10	compressor 2 circuit 2
11	reversing valve

ENG

# 4.9 Water-cooled condensing unit

# 4.9.1 Single circuit



Key	•
-----	---

1	flow switch
2	cond. water temperature probe
3	condenser
4	compressor 1
5	high pressure
6	compressor thermal protector
7	low pressure
8	compressor 2

# 4.9.2 Two circuits



Key:	
1	flow switch
2	cond. water temperature probe
2 3	condenser
4	compressor 1 circuit 1
5	high pressure
6	compressor thermal protector
7	low pressure
8	compressor 2 circuit 1
9	compressor 1 circuit 2
10	compressor 2 circuit 2
11	water pump

# 4.10 Reverse-cycle water-cooled condensing unit

# 4.10.1 Single circuit



Key:	
1	condenser probe
2	condenser
3	frost protection heater
4	compressor 1
5	high pressure
6	compressor thermal protector
7	low pressure
8	compressor 2
9	reversing valve

# 4.10.2 Two circuits





1	condenser probe
2	condenser 1 & 2
3	frost protection heater 1 & 2
	reversing valve
)	compressor 1 circuit 1
,	high pressure 1 & 2
7	compressor 1 & 2 thermal protector
	low pressure 1 & 2
)	compressor 1 circuit 2
0	compressor 2 circuit 1
1	compressor 2 circuit 2
2	water pump

Fig. 4.z

# ENG

# 5. COMMISSIONING

# 5.1 APPLICA app



The "Applica" app can be used to configure the controller from a mobile device (smartphone, tablet), via NFC (Near Field Communication) and Bluetooth (BLE). Users can both configure the commissioning parameters and set groups of preset parameters according to specific needs (recipes).

Once the Carel "Applica" app has been installed and opened (see the paragraph "Mobile device", proceed as follows:

- For NFC devices, move (A) the mobile device near to the μChiller user terminal (the position of the NFC antenna on the mobile device must be identified in order to place it over the display): wait for the signal that the device has been read (B).
- 2. 2. For Bluetooth devices (C), select the "SCAN BLUETOOTH" option, then choose the device from the list.

# 5.2 Config. procedure - Legacy model

#### 5.2.1 Step 1 - Set the refrigerant

Notice: refer to the table of models in the "Introduction".

 With Bluetooth devices, access the Service menu by clicking the icon at the bottom right (figure). With NFC devices, the Service menu is already displayed by default (figure below point 2);



2. click "Set-up"--> "Configurations" --> "Defaults" (figure);





- 3. select the refrigerant used in the unit;
- apply the selected configuration via NFC or Bluetooth. The refrigerant has now been correctly configured;

### 5.2.2 Step 2 - Configure the unit

 continue configuring the unit by clicking the "Set-up"--> "Unit setup" --> "Unit configuration". Complete the unit configuration by pressing the PREV / NEXT buttons to scroll through all of the configuration parameter pages;

11:32 🗇		11:	33 🗇	\$( 🗢 🕮
← Configuration		~	Unit Set-up	
Configurations	Q Q Q Q Q Q Q Q Q Q Q Q Q Q Q Q Q Q Q	U	Regional and the second	←→ In/Out settings
	ľ			
Clone	Change name		uC2SE	
Update FW				
11:33 😇	\$ † B			
← Unit configurat				
U077 Type of unit (0=CH, 1=HP, S068				
Source type (0=Air, 1=Wate U076 Number of users pumps	er)			
C046 No. of unit circuits	1			

2. apply the parameters configured via NFC / Bluetooth to the controller.

C047 Type of S065 Type of S064

Type of source air circuit (0=Inde

# 5.2.3 Step 3 - Configure the inputs/outputs

 click "Set-up"--> "Unit setup" --> "IO configuration". Complete the unit configuration by pressing the PREV / NEXT buttons to scroll through all of the configuration parameter pages;.

← Configuration		11:33 🖯	*.
		← Unit Set-up	
Configurations	Unit Set-up	Unit configuration	In/Out se
Clone	Change name	uc2se	
Update FW			
- *			
	\$ #1 \$ (E)		
- In/Out settings	3		
In/Out settings Analog in	3		
<ul> <li>In/Out settings</li> <li>Analog in</li> <li>c31</li> </ul>	3		
Analog in Ic31 I configuration Ic32	s 🔛		
In/Out settings     Analog in     ca1     configuration     coofiguration	s E		
<ul> <li>In/Out settings</li> <li>Analog in</li> <li>Ic31</li> <li>1 configuration</li> <li>Ic32</li> <li>2 configuration</li> <li>Ic00</li> </ul>	nput 7		
In/Out settings     Analog in     Analog in     Ic31     2 configuration     Ic32     2 configuration     Ic34	s E		
Analog in Analog in Iconfiguration Ic32 2 configuration Ic34 4 configuration	s E		
In/Out settings  Analog in  Lc31  Configuration  Lc00  3 configuration	s E		
- In/Out settings Analog in c31 configuration c32 configuration c34 a configuration c35 coofiguration c03	s E		
<ul> <li>In/Out settings</li> <li>Analog in</li> <li>configuration</li> <li>cooliguration</li> </ul>	<ul> <li>Imput</li> <li>7</li> <li>8</li> <li>0</li> <li>7</li> <li>8</li> </ul>		
Analog in Call configuration cal configuration configuration configuration cal configuration cal configuration cal configuration cal configuration cal configuration cal configuration	<ul> <li>Imput</li> <li>7</li> <li>8</li> <li>0</li> <li>7</li> <li>8</li> <li>0</li> <li>7</li> <li>8</li> <li>0</li> </ul>		

2. apply the parameters configured via NFC / Bluetooth to the controller.

# 5.2.4 Step 4 - Configure parameter compatibility with mCH2

1. click "Set-up"--> "Unit setup" --> "mCH2 parameters" and complete the configuration of the unit





2. apply the parameters configured via NFC/Bluetooth to the controller.



### 5.2.5 Applica: date and time setting

Applica includes a feature for setting the date and time on  $\mu$ Chiller in just one simple step, copying the values from the mobile device.





#### Procedure:

- 1. open Applica on the mobile device;
- access the controller via NFC or Bluetooth, entering your profile credentials;
- 3. access the menu on the command bar at the top left;
- 4. select "set date/time":
- 5. confirm;
- 6. with an NFC connection, move the device near to the user terminal to write the copied values.

Notice: with a Bluetooth connection, the values are copied on confirmation.

# 5.2.6 Applica: copy configuration

Applica includes a "Clone" feature to acquire the configuration from one unit and replicate it "one-for-one" to other units.

#### Procedure:

- 1. open Applica on the mobile device;
- 2. access the controller via NFC or Bluetooth, using the "Service" or "Manufacturer" profile credentials;
- 3. follow the path "Configurations/Clone";
- 4. enter a name to describe the configuration being saved;
- with an NFC connection: move the device bear to the display terminal on the µChiller that the configuration is being copied from; once the message shows the configuration has been acquired, this is saved to the smartphone's memory, available via icon 2 (see the following figure);
- select the saved configuration; (with an NFC connection) move the device near to the display terminal on the µChiller that the same configuration is being applied to;
- 7. confirm and wait for the confirmation message.

**Notice:** with a Bluetooth connection the configuration is saved/applied on confirmation.



With reference to the previous figure, tapping the icon:

- 1. accesses the configurations saved by the user;
- 2. accesses the configurations prepared by Carel;
- 3. accesses the saved clones.

**Notice:** follow the order shown in the table to configure the Unit set-up parameters.

Par.	Description	Def.	Min.	Max.	UOM
U077	Type of unit	0	0	6	-
	0=CH:				
	<u>иесп,</u> 1=НР:				
	2=CH/HP:				
	3=Cooling-only condensing unit;				
	4=Reverse-cycle condensing unit;				
	5=Cooling-only air/air;				
	6=Reverse-cycle air/air;				
6060		0	0	1	
S068	Source type (0=Air, 1=Water)	0	0	1	-
U076	Number of system pumps	1		2	-
C046	No. of unit circuits	1	1	2	-
C047	Type of compressors used (0=1 On/Off; 1=2 On/Off; 2=1 BLDC; 3=1 BLDC+On/Off)	0	0	1/3	-
S065	Type of source fan (0/1=Modulating/ON-OFF)	0	0	1	-
S064	Type of source air circuit (0=Independent; 1=Common)	0	0	1	-
S072	Source pump activation	0	0	1	-
	0=always on				
	1=On with compressors on				
	2=control on condensing temperature				
E047	ExV driver (0=Disabled; 1=Built-in; 2=EVD Evolution)	0	0	2	
E046	EVD Evolution: valve (1=CAREL ExV,) (*)	1	1	2	-
EU40				24	-
5020	(*) see EVD Evolution manual for the complete list of selectable valves	20.0	60.0	200.0	
E020	MOP in cooling: threshold	30.0	-60.0	200.0	
E022	MOP in heating: threshold	20.0	-60.0	200.0	°C
C017	Max high pressure threshold (HP)	65.0	0.0	999.9	
C018	Min low pressure threshold (LP)	0.2	-99.9	99.9	bar
U068	Free cooling: enable (0/1=no/yes)	0	0	1	-
U074	Free cooling type (0=Air; 1=Remote coil; 2=Water)	0	0	2	-
U071	Design free cooling delta T	8.0	0.0	99.9	K
U061	System pump overload: input logic (0/1=NC/NO)	0	0	1	-
U065	Freecooling valve: output logic (0/1=NO/NC)	0	0	1	-
S063	Reversing valve: output logic (0/1=NO/NC)	0	0	1	-
S054	4-way valve: pressure differential for reversing	3.0	0.0	999.9	bar
C049	Low pressure switch alarm delay on compressor activation	90	0	999	-
C050	Low pressure switch alarm delay with compressor on	15	0	999	-
C051	Low pressure switch input logic (0=NC; 1=NA)	0	0	1	-
S053	Defrost synchronisation (0=Independent, 1=Separate, 2=Simultaneous)	0	0	2	-
U006	Cooling set point: minimum limit	5.0	-99.9	999.9	°C
U007	Cooling set point: maximum limit	20.0	-99.9	999.9	°C
U008	Heating set point: minimum limit	30.0	0.0	999.9	°C
U009	Heating set point: maximum limit	45.0	0.0	999.9	°C
Hc13	Buzzer (0/1=No/Yes)	1	0	1	-
U081	High/low pressure and frost alarm reset configuration	7	0	7	-
	0= HP1-2/LP1-2/A1-2/Manual frost protection				
	1=HP1-2/LP1-2/A1-2/Automatic frost protection				
	2 = HP1-2/A1-2 Manual frost protection LP1-2 automatic				
	3= HP1-2 manual LP1-2/A1-2 Automatic frost protection				
	4= HP1-2/LP1-2 manual LP1-2/Altomatic frost protection				
	5= HP1-2/LP1-2 (3 times in an hour) manual; A1-2/Automatic frost protection				
	6= HP1-2/LP1-2 (3 times in an hour) manual; A1-2/Automatic frost protection 6= HP1-2/LP1-2 (3 times in an hour) manual; A1-2/Manual frost protection				
	7=HP1-2 manual/LP1-2 (3 times in an hour)/Manual frost protection				Tab 5 a

(\*) see EVD Evolution manual for the complete list of selectable valves

Tab. 5.a

**ENG** 

# 5.3.2 I/O configuration

For the description of the following parameters, see chapter 3 of this document

HC32 / A HC00 / A HC34 / A HC35 / A HC03 / A HC04 / A HC41 / A HC42 / A HC42 / A HC42 / A HC44 / A HC45 / A HC45 / A HC47 / A HC47 / A	Analogue input 1 configuration Master Analogue input 2 configuration Master Analogue input 3 configuration Master Analogue input 4 configuration Master Analogue input 5 configuration Master Analogue input 7 configuration Master Analogue input 1 configuration Slave Analogue input 2 configuration Slave Analogue input 2 configuration Slave Analogue input 3 configuration Slave Analogue input 4 configuration Slave Analogue input 5 configuration Slave Analogue input 5 configuration Slave Analogue input 5 configuration Slave Analogue input 6 configuration Slave Analogue input 7 configuration Slave Digital input 1 configuration Master	7 8 0 7 8 0 6 0 0 0 0 7 8 8 0	0 0 0 0 0 0 0 0 0 0 0 0 0 0	8 8 10 10 11 8 8 8 8 8 8 10 10	- - - - - - - - - - - - - - - -
HC32 / A HC00 / A HC34 / A HC35 / A HC03 / A HC04 / A HC41 / A HC42 / A HC42 / A HC42 / A HC44 / A HC45 / A HC47 / A HC47 / A	Analogue input 2 configuration Master Analogue input 3 configuration Master Analogue input 4 configuration Master Analogue input 5 configuration Master Analogue input 6 configuration Master Analogue input 7 configuration Master Analogue input 1 configuration Slave Analogue input 2 configuration Slave Analogue input 3 configuration Slave Analogue input 4 configuration Slave Analogue input 5 configuration Slave Analogue input 5 configuration Slave Analogue input 7 configuration Slave	0 7 8 0 6 0 0 0 7 7 8	0 0 0 0 0 0 0 0 0 0 0 0	8 10 10 11 8 8 8 8 8 8 10	- - - - - - - - - -
HC34         A           HC35         A           HC03         A           HC04         A           HC41         A           HC42         A           HC43         A           HC44         A           HC45         A           HC45         A           HC47         A           HC47         A           HC41         C	Analogue input 4 configuration Master Analogue input 5 configuration Master Analogue input 6 configuration Master Analogue input 7 configuration Master Analogue input 1 configuration Slave Analogue input 2 configuration Slave Analogue input 3 configuration Slave Analogue input 4 configuration Slave Analogue input 5 configuration Slave Analogue input 5 configuration Slave Analogue input 6 configuration Slave	7 8 0 6 0 0 0 7 8	0 0 0 0 0 0 0 0 0 0	10 10 11 8 8 8 8 8 8 10	- - - - -
HC34         A           HC35         A           HC03         A           HC04         A           HC41         A           HC42         A           HC43         A           HC44         A           HC45         A           HC45         A           HC47         A           HC47         A           HC41         C	Analogue input 4 configuration Master Analogue input 5 configuration Master Analogue input 6 configuration Master Analogue input 7 configuration Master Analogue input 1 configuration Slave Analogue input 2 configuration Slave Analogue input 3 configuration Slave Analogue input 4 configuration Slave Analogue input 5 configuration Slave Analogue input 5 configuration Slave Analogue input 6 configuration Slave	8 0 6 0 0 0 7 8	0 0 0 0 0 0 0 0	10 11 8 8 8 8 8 10	- - - - -
HC35         A           HC03         A           HC04         A           HC41         A           HC42         A           HC43         A           HC44         A           HC45         A           HC45         A           HC47         A           HC47         A           HC47         A           HC47         A	Analogue input 5 configuration Master Analogue input 6 configuration Master Analogue input 7 configuration Master Analogue input 1 configuration Slave Analogue input 2 configuration Slave Analogue input 3 configuration Slave Analogue input 4 configuration Slave Analogue input 5 configuration Slave Analogue input 6 configuration Slave Analogue input 7 configuration Slave	0 6 0 0 0 7 8	0 0 0 0 0 0	11 8 8 8 8 10	- - - - -
HC03         A           HC04         A           HC41         A           HC42         A           HC43         A           HC44         A           HC45         A           HC45         A           HC45         A           HC45         A           HC47         A           HC47         A           HC14         C	Analogue input 6 configuration Master Analogue input 7 configuration Master Analogue input 1 configuration Slave Analogue input 2 configuration Slave Analogue input 3 configuration Slave Analogue input 4 configuration Slave Analogue input 5 configuration Slave Analogue input 6 configuration Slave Analogue input 7 configuration Slave	6 0 0 7 8	0 0 0 0 0	8 8 8 8 10	
HC41 / HC42 / HC43 / HC43 / HC44 / HC45 / HC45 / HC47 / HC14 [	Analogue input 1 configuration Slave Analogue input 2 configuration Slave Analogue input 3 configuration Slave Analogue input 4 configuration Slave Analogue input 5 configuration Slave Analogue input 6 configuration Slave Analogue input 7 configuration Slave	0 0 0 7 8	0 0 0 0	8 8 8 10	
HC41 / HC42 / HC43 / HC43 / HC44 / HC45 / HC45 / HC47 / HC14 [	Analogue input 1 configuration Slave Analogue input 2 configuration Slave Analogue input 3 configuration Slave Analogue input 4 configuration Slave Analogue input 5 configuration Slave Analogue input 6 configuration Slave Analogue input 7 configuration Slave	0 0 7 8	0 0 0	8 8 10	-
HC43 A HC44 A HC45 A HC05 A HC47 A HC14 [	Analogue input 3 configuration Slave Analogue input 4 configuration Slave Analogue input 5 configuration Slave Analogue input 6 configuration Slave Analogue input 7 configuration Slave	0 7 8	0 0 0	8 10	-
HC43 A HC44 A HC45 A HC05 A HC47 A HC14 D	Analogue input 3 configuration Slave Analogue input 4 configuration Slave Analogue input 5 configuration Slave Analogue input 6 configuration Slave Analogue input 7 configuration Slave	7 8	0	10	
HC44 A HC45 A HC05 A HC47 A HC14 [	Analogue input 4 configuration Slave Analogue input 5 configuration Slave Analogue input 6 configuration Slave Analogue input 7 configuration Slave	8	0		-
HC45 / HC05 / HC47 / HC14 [	Analogue input 5 configuration Slave Analogue input 6 configuration Slave Analogue input 7 configuration Slave			10	
HC05 A HC47 A HC14 [	Analogue input 6 configuration Slave	0		1 10	-
HC47 A HC14 [	Analogue input 7 configuration Slave		0	11	-
HC14 [		6	0	8	-
		1	0	12	-
HC15 E	Digital input 2 configuration Master	2	0	12	-
	Digital input 4 configuration Master	0	0	12	-
	Digital input 5 configuration Master	7	0	12	-
	Digital input 6 configuration Master	6	0	12	-
	Digital input 1 configuration Slave	10	0	12	-
	Digital input 2 configuration Slave	2	0	12	-
	Digital input 4 configuration Slave	0	0	12	-
	Digital input 5 configuration Slave	7	0	12	-
	Digital input 6 configuration Slave	0	0	12	-
	Analogue output 1 configuration Master	1	0	3	-
	Analogue output 2 configuration Master	3	0	3	-
	Analogue output 1 configuration Slave	1	0	3	-
	Analogue output 2 configuration Slave	0	0	3	-
	Digital output 1 configuration Master	1	0	12	-
	Digital output 2 configuration Master	2	0	12	-
	Digital output 3 configuration Master	4	0	12	-
	Digital output 4 configuration Master	7	0	12	-
	Digital output 5 configuration Master	10	0	12	-
HC56 [	Digital output 6 configuration Master	0	0	12	-
HC61 [	Digital output 1 configuration Slave	1	0	8	-
	Digital output 2 configuration Slave	2	0	8	-
	Digital output 3 configuration Slave	4	0	8	-
HC64 [	Digital output 4 configuration Slave	7	0	8	-
HC65 [	Digital output 5 configuration Slave	0	0	8	-
HC66	Digital output 6 configuration Slave	0	0	8	-
	Evaporation pressure:	0	0	1	-
	probe type (0=0-5V; 1=4-20mA)				
	Evaporation pressure probe: min value	0.0	-1.0	99.9	bar
	Evaporation pressure probe: max value	17.3	0.0	99.9	bar
	Condensing pressure:	0	0	1	-
	probe type (0=0-5V; 1=4-20mA)				
	Condensing pressure probe: min value	0.0	-1.0	99.9	bar
	Condensing pressure probe: max value	45.0	0.0	99.9	bar
			2.0		Tab. 5.b

# mCH2 parameters

5.3.3

Par.	Description	Def.	Min.	Max.	UOM
F027	Compressors at part load (0=NO, 1=YES)	0	0	1	-
F003	Number of evaporators (0=1; 1=2)	0	0	1	-
F007	Sensor S4 installed on the source heat	0	0	1	-
	exchanger (0=No, 1=Yes: in CH mode				
	reads condensing temp., in HP mode				
	reads evap. temp.)				
F008	Frost protection alarm delay	10	0	999	-
F009	Supply air temperature limit threshold	14.0	0.0	99.9	°C
F010	Supply air temperature limit diff.	4.0	0.0	20.0	°K
F011	Heater dig. output logic (0=NO; 1=NC)	0	0	1	-
F012	Offset on set point in	1.0	0.0	99.9	°K
	cooling operation for the heaters				
F013	Differential on set point in cooling mode	0.5	0.2	99.9	°K
	for the heaters				
F014	Offset on set point in	3.0	0.0	99.9	°K
	heating mode for the heaters				
F015	Differential on set point in heating mode	1.0	0.2	99.9	°K
	for the heaters				
F016	Heaters active during defrost	0	0	1	-
	(0=No, 1=Yes)				
F017	Supply fan operating mode (0=Always	0	0	1	-
	ON: 1=ON				
	by temp. control)				
F018	Hot-start set point	40.0	0.0	99.9	°C
F019	Hot-keep differential	5.0	0.0	99.9	°K
F020	Compressor request logic	1	0	1	-
	from digital input (0=NC; 1=NO)				
F021	Mixed water outlet temperature	0.0	-99.9	99.9	°K
	probe calibration (S1 expansion)				
F022	Evaporator 2 water outlet temperature	0.0	-99.9	99.9	°K
	probe calibration (S2 expansion)				
F023	Direct relationship between digital	0	0	1	-
. 020	inputs	Ŭ	Ū		
	and digital outputs for				
	condensing unit (0=No, 1=Yes)				
F024	Manual heater 1 management	0	0	2	
1024	(0=AUTO; 1=OFF; 2=ON)		0	_ <i>_</i>	
F025	Manual heater 2 management	0	0	2	_
1023	(0=AUTO; 1=OFF; 2=ON)		U	2 ×	-
F026	Compressors off at low outside temper-	-40.0	-40.0	99.9	°C
020		-40.0	-40.0	99.9	
	ature (air/air)				Tab. 5.c

# CAREL

# 5.4 Applica Desktop

Applica Desktop is a program intended for manufacturers and installers of units fitted with the  $\mu$ Chiller controller. It can be downloaded from ksa. carel.com.

The Applica Desktop offers the possibility to:

- access the controller using the assigned profile;
- create configurations;
- apply configurations;
- clone a unit configuration, i.e. copy all of the unit's parameter values;
- complete the commissioning procedure;
- troubleshoot any problems on the unit.

#### Note:

- Applica Desktop can be used as an alternative to the Applica app, and requires an internet connection;
- For the physical connection to the BMS port on  $\mu\text{Chiller},$  use the USB/ RS485 converter P/N CVSTDUMOR0



Fig. 5.b

#### 5.4.1 Preparing for operation

- 1. Access KSA, "Software & Support","µChiller" section.
- 2. Select the "Configurations" folder.
- For μChiller Standard, Enhanced and Legacy models (with On/ Off compressor), select the "Refrigerants" section and then the refrigerant charged on the unit.
- Connect to the BMS port on the µChiller controller, as shown in Figure 5.b;
- 5. Open Applica Desktop; a window will be opened with the right part of the top bar as shown below:

📴 🔛 🔹	CAREL ApplicaDesktop
File Target	
■ β <sup>G</sup> Connect	
<ul> <li>*</li></ul>	
∓ ×o Remove	
Tarpets	

- 6. Select "Add target" and assign it a meaningful name (e.g.
- In the "COM Port" field, enter the COM port used for the USB connection to the USB/RS485 converter;
- Configure the connection parameters (Baudrate=115200, Bits=8, Parity=None, Stop Bits=Two, Serial Node=1) as shown in the figure (the data are saved automatically);
- 9. Use "Connect" to connect to the  $\mu\text{Chiller}$  (which must be powered on).

		COM Port Baudrate	COM5 11520		Parity Stop Bit	None Two	•		
		Bits	8		Target	1			
			-	Properties					
12 ·								CAR	EL ApplicaD
File Target									
uChiller	Info		COM Port	COM5	- Parity	None	Security		
· · · Add Target	Name	uChiller	Baudrate	115200	· Stop Bits	Тию	Encryption	None	
A Long wilder									
₹ ×o Remove	Communication Type	Serial -	Bits	8	- Target	1	Password		_

# 5.5 Configuration procedure with Applica Desktop - Legacy Model

### 5.5.1 Step 1 - Set the refrigerant

Once connected, select the "Configurations" label: the command bar will be displayed, as shown:

📴 🔛 🕫									CAREL ApplicaDesktop
File Target Configu	rations	Tags							
√ (None) ▲ ▼ ▼	*S	Edit	Apply Configuration •	S File	Compare				
Configurations		-		🎾 Import		1000	00.1	 	
C003		Compr.	2 circ.1 maintei	32 Export	threshold (	x100)	99 h		
C005		Compr	2 circ 1 manual		iπo 1-0	EE 2-OND	0		

- 1. Select "File -> Import" to load the refrigerant configurations downloaded from KSA;
- Select the configuration to be applied to the μChiller, and then "Apply Configuration";

📴 🔛	÷		CAREL ApplicaDesktop
File	Target Configurations Tags		
(None)	RefrP2T_R410A	* S S Apply New Edit Apply File Compare	
	Configurations		

3. Applica Desktop will display a message when the parameters have been set, and if necessary indicating any values that have been applied that do not belong to the current user profile (some parameters may not be visible to the user).

# 5.5.2 Step 2 - Configure µChiller

 Select the "Configurations" label, select "New -> New configuration" and assign a name to the new configuration being created.

📴 🔛 👼 Ŧ					CAREL Ap	plicaDeskt	op v1.0.877.14911
File Target Configuration	ns Tags						
Vince)	ration1 🛱 🗌 Configuration2 🚮	New	Edit Apply Configuration -	File	Compare		
Conf	figurations	⁺¢ Ne	w configuration				
Name De	escription	🏂 Ne	w cloned configuration				Value
Coc eD	c						() BC

- 2. Select the newly created configuration
- Select "Edit -> Apply Live Values". This operation copies the values of the parameters currently saved on the connected µChiller to the newly created configuration.

2 🔛 🗗 ÷			CAREL Applical	esktop v1.0.877.14911					– ø ×
File Target	Configurations Tags								~ (
(None)	Configuration1 🗰 🗹 Configuration2 🛐 👘	ide Apply File Configuration	Compare						
	Configurations	Q Apply default values							
Name	Description			Value	Configuration value	Default value	Type	Limits	
		Apply live values		varue	Configuration value	Dendunt value	type	Limita	Tags
	0:				Dic Configuration value		i)pe	illinis illinis	=
O HC	Comp. 1 circuit 1: maintenance hour threshold	d Clear			-		UINT		Compressor Maint
С000	•	d Clear	)	Dec.	Dec	Dec	0	·0:	-
0× C000 C002	Comp. 1 circuit 1: maintenance hour threshold	✓ Clear ☐ Duplicate		Dec.	Dec	0=c 99 h	UINT	0.999	Compressor Maint
©× C000 C002 C003 C005	Comp. 1 circuit 1: maintenance hour threshold Comp. 1 circuit 1: operating mode (0=AUTO, 1=DFF,	<ul> <li>✓ Clear</li> <li>Duplicate</li> <li>₩ Remove</li> </ul>		0⊯⊂ 99 h 0	0	0⊫⊂ 99 h 0	UINT USINT	©: 0.999 0.2	Compressor Maint

- 4. Select the "Tags" label and then the "Unit\_Cfg" command
- 5. Change the parameters listed in the "Configuration value" column to configure the unit

ENG

# CAREL

📴 🔛 😚	Ŧ						(	CAREL ApplicaDesk	top v1.0.877.14911						-	٥	×
File Ta	iget Configur	ations Tags															^ <b>0</b>
(None)	BLDC	BMS	Compressor	Env	IO,CFG	MainRegul	Maint	MC	Plant Pro	obe	Ped	Select all					
Source	SourceA	SourceOfr	SourceW	Synoptic	UC2SE	Unit_Op	Unit_Setup	)				Unselect all					
						Tags											
Name		Description							Value	0	Configuration value	Default value	Туре	Limits	Tags		
T Dec		<ul> <li>•O:</li> </ul>							D=	0	×	D×	<ul> <li>O:</li> </ul>	< <b>D</b> <	-		
E022		MOP in heatin	g: threshold						20 °C	2	20 °C	20 °C	REAL	-60200	Exv Unit	Ctg	
E023		MOP in heatin	g: Ti						15 s	1	15 s	15 s	REAL	0.800	Exv Unit	Ctg	_

- 6. Repeat the same steps for the "IO\_CFG" and "uCH2SE" tags.
- 7. The unit has now been configured. If desired, the control parameters can be modified using the other tags available as search filters.
- 8. Once all of the desired parameters have been changed, to apply the changes select the "Configuration" label and select "Apply Configuration"

🔤 😫 🔹		CAREL ApplicaDesktop
File Target Configurations Tags	$\frown$	
(None)	*s     *s     *s     *s       New     Edit     Apply Configuration     File     Compare	
Configurations		

Finally, to save the newly-created configuration for future use, from the "Configurations" label select "File -> Export" and assign a name to the configuration being saved.

Ŷ	🔛 🚰 Ŧ				CAREL ApplicaDesk	top v1.0.877.14911
	File Target Configura	ations Tags				
	(None) Confi	iguration1 🗰 🗹 Configuration2 📰 🍝	⁺ <b>\$ \$</b> New Edit	Apply Configuration -		
	c	Configurations		92 In	mport	
	Name	Description		🎾 B	xport	Value
т	∎ec .	4 <b>0</b> 4				<b>⊡</b> ac

# 5.5.3 Applica Desktop: date and time setting

Applica Desktop can set the date and time on  $\mu Chiller$  in just one simple step, copying the values from the PC to the controller.

🚾 🔛 💏 🔻							CAREL ApplicaDesktop v1.0.877.14911					
File Target	Configurations	Tags										
√ Target1	Disconnect	Info		COM Port	COM4 •	Parity	None •	Security			$\frown$	
v myerr	* D Add Target	Name	Target1	Baudrate	57600 *	Stop Bits	One •	Encryption None *	0	,	÷	1
	₹ <sup>×</sup> ë Remove	Communication Type	Serial	<ul> <li>Bits</li> </ul>	8 -	Device Address	1	Password	-		_	Export values log
Targets		Properties							Information	Download	Set date/time	Parameters
											$\overline{}$	

Procedure:

- 1. Once connected, select "Set date&time";
- 2. In the pop-up window, confirm synchronisation of the time and date on  $\mu\text{Chiller}$  with the PC








#### CAREL INDUSTRIES - Headquarters

Via dell'Industria, 11 - 35020 Brugine - Padova (Italy) Tel. (+39) 049.9716611 - Fax (+39) 049.9716600 e-mail: carel@carel.com - www.carel.com Agenzia / Agency: